


如何在 Mac 上更新 GR10 4K@120Hz 韌體

1. 下載安裝包，並解壓縮



2. 將解壓縮後的資料夾放在「桌面」
3. 將 GR10 接上 mac
4. 在 mac 上叫出終端機 Terminal
5. 輸入 `cd ~/Desktop`

```
benq@B-55639 ~ % cd ~/Desktop  
benq@B-55639 Desktop %
```

6. 輸入 `cd GR10_MAC_4K120`

```
benq@B-55639 Desktop % cd GR10_MAC_4K120  
benq@B-55639 GR10_MAC_4K120 %
```

7. 可再輸入 `pwd` 指令，確認當前所在目錄，應顯示類似於：
/Users/您的使用者名稱/Desktop/GR10_MAC_4K120

```
benq@B-55639 GR10_MAC_4K120 % pwd  
/Users/benq/Desktop/GR10_MAC_4K120  
benq@B-55639 GR10_MAC_4K120 %
```

8. 輸入 `./RTKTool_C /U BENQ_GR10_RTD2175_USER_V2p10_CRC.bin`
讓他執行更新程序，直到 Update success 出現，即為更新完成（等待約 2 分鐘）


```
benq@B-55639 GR10_MAC_4K120 % ./RTKTool_C /U BENQ_GR10_RTD2175_USER_V2p10_CRC.bin  
IOCreatePlugInInterfaceForService result:(os/kern) successful  
Update Success  
benq@B-55639 GR10_MAC_4K120 %
```

9. 輸入 `./RTKTool_C /R` 確定版本是否正確: 2.10

```
benq@B-55639 GR10_MAC_4K120 % ./RTKTool_C /R  
IOCreatePlugInInterfaceForService result:(os/kern) successful  
Success:2.10  
benq@B-55639 GR10_MAC_4K120 %
```

How to upgrade GR10 4K@120Hz Firmware for Mac

1. Download the installation package and unzip it.



2. Place the unzipped folder on the "Desktop."
3. Connect the GR10 to the Mac.
4. Open the Terminal on the Mac.
5. Enter `cd ~/Desktop`

```
benq@B-55639 ~ % cd ~/Desktop
benq@B-55639 Desktop %
```

6. Enter `cd GR10_MAC_4K120`

```
benq@B-55639 Desktop % cd GR10_MAC_4K120
benq@B-55639 GR10_MAC_4K120 %
```

7. You can then enter the `pwd` command to confirm your current directory. It should display something like:

/Users/Name/Desktop/GR10_MAC_4K120

```
benq@B-55639 GR10_MAC_4K120 % pwd
/Users/benq/Desktop/GR10_MAC_4K120
benq@B-55639 GR10_MAC_4K120 %
```

8. Enter `./RTKTool_C /U BENQ_GR10_RTD2175_USER_V2p10_CRC.bin`

This command will run the update process. Wait until "Update success" appears to confirm the update is complete (approximately 2 minutes).

```
benq@B-55639 GR10_MAC_4K120 % ./RTKTool_C /U BENQ_GR10_RTD2175_USER_V2p10_CRC.bin
IOCreatePlugInInterfaceForService result:(os/kern) successful
Update Success
benq@B-55639 GR10_MAC_4K120 %
```

9. Enter `./RTKTool_C /R` to verify if the firmware version is correct: 2.10

```
benq@B-55639 GR10_MAC_4K120 % ./RTKTool_C /R
IOCreatePlugInInterfaceForService result:(os/kern) successful
Success:2.10
benq@B-55639 GR10_MAC_4K120 %
```

Notes:

1. There may be unforeseen compatibility issues after updating the custom macOS firmware, as this is a test version and has not undergone full compatibility testing.
2. If the custom macOS firmware causes any issues, please revert to the regular firmware.